



US007782309B2

(12) **United States Patent**
Janik

(10) **Patent No.:** **US 7,782,309 B2**
(45) **Date of Patent:** ***Aug. 24, 2010**

(54) **CONTROLLING DEVICE WITH
DUAL-MODE, TOUCH-SENSITIVE DISPLAY**

(75) Inventor: **Craig M. Janik**, Los Altos Hills, CA
(US)

(73) Assignee: **Universal Electronics Inc.**, Cypress, CA
(US)

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 155 days.

This patent is subject to a terminal dis-
claimer.

(21) Appl. No.: **12/103,895**

(22) Filed: **Apr. 16, 2008**

(65) **Prior Publication Data**

US 2008/0191898 A1 Aug. 14, 2008

Related U.S. Application Data

(63) Continuation of application No. 11/290,358, filed on
Nov. 30, 2005, now Pat. No. 7,432,916.

(60) Provisional application No. 60/634,680, filed on Dec.
9, 2004.

(51) **Int. Cl.**
G09G 5/00 (2006.01)

(52) **U.S. Cl.** **345/173; 348/734**

(58) **Field of Classification Search** **345/173,**
345/156, 169; 348/14.02, 14.03, 14.05, 734;
340/5.61, 825.22; 715/700, 717; 178/18.01;
341/176; 386/83

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,623,887 A 11/1986 Welles, II

4,959,810 A	9/1990	Darbee et al.	
5,255,313 A	10/1993	Darbee	
5,481,256 A	1/1996	Darbee et al.	
5,552,917 A	9/1996	Darbee et al.	
5,614,906 A	3/1997	Hayes et al.	
5,724,567 A	3/1998	Rose et al.	
5,758,257 A	5/1998	Herz et al.	
5,884,028 A	3/1999	Kindell et al.	
5,926,624 A	7/1999	Katz et al.	
5,959,751 A	9/1999	Darbee et al.	
6,014,092 A	1/2000	Darbee et al.	
6,137,479 A	10/2000	Olsen et al.	
6,225,938 B1	5/2001	Hayes et al.	
6,700,893 B1	3/2004	Radha et al.	
6,708,213 B1	3/2004	Bommaiah et al.	
6,794,992 B1	9/2004	Rogers	
6,914,551 B2 *	7/2005	Vidal	341/176
7,117,516 B2	10/2006	Khoo et al.	
7,283,084 B2 *	10/2007	Di Peppe	341/176
7,432,916 B2 *	10/2008	Janik	345/173
2003/0025840 A1	2/2003	Arling	
2003/0103088 A1	6/2003	Dresti et al.	


* cited by examiner

Primary Examiner—Abbas I Abdulsalam
(74) *Attorney, Agent, or Firm*—Greenberg Traurig, LLP

(57) **ABSTRACT**

A universal controlling device having a touch-sensitive display. The display provides one or more graphical user interfaces comprised of graphical user interface icons that are selectable via the touch-sensitive display and the display accepts motions made by a stylus or finger in contact with the touch-sensitive display. The different interactions with the touch-sensitive display are used to cause the transmission of respective data to one or more appliances.

8 Claims, 4 Drawing Sheets






FIGURE 1




FIGURE 2




FIGURE 3




FIGURE 4

CONTROLLING DEVICE WITH DUAL-MODE, TOUCH-SENSITIVE DISPLAY

RELATED APPLICATION DATA

This application claims the benefit of and is a continuation of U.S. application Ser. No. 11/290,358, filed on Nov. 30, 2005, which, in turn, claims the benefit of U.S. Application No. 60/634,680, filed on Dec. 9, 2004.

BACKGROUND

The following relates generally to controlling devices and, more particularly, to a controlling device having a dual-mode, touch-sensitive display.

Manufacturers typically provide a controlling device with an appliance and, as such, different appliance types of different manufacturers are often commanded with different controlling devices, also referred to as "remote controls." To minimize the number of individual controlling devices a user requires, universal controlling devices have been developed. Accordingly, universal controlling devices for commanding various operational functions of various types of appliances of various manufacturers have become quite widespread. By way of example, universal controlling devices are described in commonly assigned U.S. Pat. Nos. 4,959,810, 5,255,313 and 5,552,917.

For selecting which of multiple appliances a universal controlling device is to command, a universal controlling device may allow a user to place, i.e., configure, the universal controlling device into an operational mode whereby the function keys will be used to transmit commands to a "primary" target appliance that has been associated with that operational mode. For example, a "TV" operational mode may be selected to place the universal controlling device into an operational mode whereby function keys are used to transmit commands primarily to a designated television, a "VCR" mode may be selected to place the universal controlling device into an operational mode whereby function keys are used to transmit commands primarily to a designated VCR, etc. A universal controlling device may also be provided with an ability to be configured in a "home theater" operational mode (i.e., one established to facilitate a particular activity), a "user" operational mode (i.e., one established for a particular user), a "room" operational mode (i.e., one established for a particular room), or the like (collectively referred to hereinafter as a "home theater" operational mode). In a "home theater" operation mode, the universal controlling device will generally be adapted to command multiple target appliances. For example, a "home theater" mode may be established whereby volume function keys are used to transmit volume control commands to an amplifier, transport function keys are used to transmit transport control commands to a VCR, channel function keys are used to transmit channel control commands to a cable box, picture control function keys are used to transmit picture control commands to a television, etc.

In the case of universal controlling device having a display, various function keys, such as those appropriate for the various operational modes, are typically presented to a user in multiple, different user interfaces each comprising one or more displayed soft keys. For example, commonly assigned U.S. Published Patent Application No. 2003/0103088 (Ser. No. 10/288,727) discloses a universal controlling device application for use in connection with a hand-held device having a display, e.g., a personal digital assistant ("PDA"), wherein the display is utilized to present the multiple, different user interfaces. While the use of a display advantageously

allows a universal controlling device to present multiple, different user interfaces to allow for the command of operational functions of one or more appliances, what is needed is a universal controlling device wherein the display is further adapted to provide remote, cursor control functionality.

SUMMARY

In accordance with this and other needs, the following generally discloses a universal controlling device having a dual-mode, touch-sensitive display which is switchable between two operational modes. In one operational mode, the display provides one or more graphical user interfaces comprised of graphical user interface icons that are selectable to a second operational mode, the display provides pointer control where motions made by a stylus or finger in contact with the touch-sensitive display result in corresponding motions of a pointer on a display located remotely from the universal controlling device, such as a display connected with a personal computer, a TV, or the like.

A better appreciation of the objects, advantages, features, properties, and relationships of the disclosed controlling devices will be obtained from the following detailed description and accompanying drawings which set forth illustrative embodiments which are indicative of the various ways in which the principles described hereinafter may be employed.

BRIEF DESCRIPTION OF THE DRAWINGS

For use in better understanding the exemplary universal controlling device described hereinafter reference may be had to the following drawings in which:

FIG. 1 illustrates a block diagram of exemplary components of an exemplary universal controlling device;

FIG. 2 illustrates an isometric view of an exemplary universal controlling device constructed utilizing the components of FIG. 1;

FIG. 3 illustrates an exemplary system environment in which the exemplary universal controlling device of FIG. 2 may be utilized; and

FIG. 4 illustrates an exemplary flow of data within the exemplary system environment of FIG. 3.

DETAILED DESCRIPTION

The following discloses a controlling device **100** having a dual-mode, touch-sensitive face panel. In one operational mode of the controlling device **100**, the face panel is utilized to accept input to cause a transmission of at least one command to at least one appliance. In a second operational mode of the controlling device **100**, the face panel is utilized to accept input for the purpose of controlling a cursor or pointer on a larger, second device, such as a personal computer, television, or the like.

To provide the dual modes of operation, the controlling devices **100** may include, as needed for a particular application, a processor **300** coupled to a ROM memory **304**, a key matrix **340** (e.g., a touch-sensitive surface **344** placed over a liquid crystal display (LCD) alone or in combination with hard keys **342** (LCD)), transmission circuit(s) **310**, receiver circuit(s) **308** and/or transceiver circuit(s) (e.g., IR and/or RF), a non-volatile read/write memory **306**, a means **302** to provide feedback to the user (e.g., LED, display, speaker, and/or the like), a means **315** (such as a microphone, etc.) for receiving additional non-keypress input from the user, and means for providing visual and/or audio cues to the user, as

illustrated in FIG. 1. The means for providing visual and/or audio cues to the user, to disseminate information to the user, may be embodied as key illumination means, a sound or voice synthesizer circuit, and/or a digital recording and playback circuit (e.g., to allow a user to playback sound or voice tags input via a microphone or otherwise downloaded into the controlling device). The key illumination means may be in the form of separate elements, such as LEDs **320**, **322**, and **324**, either directly associated with a hard key matrix **342**. In the case where the controlling device **100** includes hard keys, an exemplary molded-in key **332** is shown as operative with key matrix circuit **330,331**.

To control the operation of the controlling device **100**, the ROM memory **304** may include executable instructions that are intended to be executed by the processor **300**. In this manner, the processor **300** may be programmed to control the various electronic components within the remote control **100**, e.g., to monitor a power supply (not shown), to cause the transmission of signals, control the key illumination means **320**, **322**, and **324**, sound circuits, etc. The non-volatile read/write memory **306**, for example an EEPROM, battery-backed up RAM, Smart Card, memory stick, or the like, may be provided to store setup data and parameters as necessary. While the memory **304** is illustrated and described as a ROM memory, memory **304** can also be comprised of any type of readable media, such as ROM, RAM, SRAM, FLASH, EEPROM, or the like. Preferably, the memory **304** is non-volatile or battery-backed such that data is not required to be reloaded after battery changes. In addition, the memories **304** and **306** may take the form of a chip, a hard disk, a magnetic disk, and/or an optical disk.

To cause the controlling device **100** to perform an action, the controlling device **100** is adapted to be responsive to events, such as a sensed user interaction with the touch pad overlaying the key matrix **344**, interaction with the hard key matrix **342**, receipt of a transmission via receiver **308**, etc. In response to an event, appropriate instructions within the memory **304** may be executed. For example, when a function command key is activated on the controlling device **100**, the controlling device **100** may retrieve a command code corresponding to the activated function command key from memory **304** and transmit the command code to an intended target appliance in a format recognizable by that appliance.

It will be appreciated that the instructions within the memory **304** can be used not only to cause the transmission of command codes and/or data to the appliances, but also to perform local operations. While not limiting, local operations that may be performed by the controlling device **100** may include displaying information/data, favorite channel setup, macro key setup, function key relocation, user programming of favorite channel selections, etc. A further, local operation is the ability to "lock" function keys across device operational modes as described in previously referenced U.S. Published Patent Application No. 2003/0025840. Examples of still further local operations can be found in U.S. Pat. Nos. 5,481,256, 5,959,751, and 6,014,092.

For creating a correspondence between a command code and a function command key, data may be entered into the controlling device **100** that functions to identify an intended target appliances by its type and make (and sometimes model). Such data allows the controlling device **100** to transmit recognizable command codes in the format appropriate for such identified appliances. Typically, intended target appliances are identified for each operational mode of the controlling device **100**. Since methods for setting up a controlling device to command the operation of specific home appliances are well-known, such methods need not be

described in greater detail herein. Nevertheless, for additional information pertaining to setup procedures, the reader may turn to U.S. Pat. Nos. 4,959,810, 5,614,906, and 6,225,938. It will also be appreciated that a controlling device **100** may be set up to command an appliance **102** by being taught the command codes needed to command such appliance as described in U.S. Pat. No. 4,623,887. Still further, it will be understood that command codes may be pre-stored in the controlling device **100** or the controlling device **100** may be upgradeable, for example via use of receiver **308**.

As illustrated in FIG. 3, the universal controlling device **100** may be utilized to command functional operations of multiple appliances, such as those typically found in a home entertainment center. Thus, appliances controllable by the universal controlling device **100** may include VCRs **400**, DVD and CD players **402**, cable set-top boxes and satellite receivers **404**, AV receivers **406**, televisions **408**, as well as lighting, heating, etc. without limitation. Typically, commands are transmitted to such appliances using an IR protocol. The universal controlling device **100** may also be utilized to command functional operations of a home theater personal computer ("HTPC") **410**. An HTPC **410** is typically a PC that is set up at the home entertainment center and is used mainly for home entertainment functions such as for playing back music and video files, playing DVDs, and for viewing digital photos. The HTPC **410** may be connected to the Internet and may also be used for viewing Internet browser content, such as news, email, search results, and the like. Preferably, the universal controlling device **100** utilizes an RF protocol when communicating with the HTPC **410** which allows for communications beyond line-of-sight. In this regard, as illustrated in FIG. 4, communications with the HTPC **410** may be made by means of a USB RF transceiver converter **412**. The USB converter device **412** includes a converting microcontroller and antenna for receiving and converting a data-stream transmitted in the RF domain by the universal controlling device **100** into USB messages for transmission to the HTPC **410**.

Turning to FIG. 2, an exemplary embodiment of a universal controlling device **100** is illustrated. In the illustrated embodiment, the various components of FIG. 1 are enclosed within a housing **502** which also provides access to various of the hard keys **342** and the touch screen display in the form of a dual-mode touch-sensitive display **504**. By way of further example, the touch-sensitive display **504** may be 320x240 pixel LCD with a clear touch-sensitive digitizing layer covering the display. As will be well understood, the touch-sensitive display **504** is supported by circuitry which provides the position of a stylus **506** (storable within the housing **502**) or finger in contact with touch-sensitive digitizer layer to a microprocessor, i.e., a touch-sensitive digitizing sub-system that provides locations and motions of a stylus or finger in contact with touch-sensitive digitizing layer to the operating system and application software for the purpose of allowing the user to control the software application. As further illustrated in FIG. 2, the universal controlling device **100** may also include a plurality of hard keys or mechanical buttons **342** or controlling various functions on target devices. It is to be understood that the function of the mechanical buttons **342** may change based on the mode of the universal controlling device **100** to thereby allow activations of the mechanical buttons to control various functions on various of the target devices.

For providing dual-mode functionality, the application software of the universal controlling device **100** preferably includes instructions which allow the touch-sensitive digitizer sub-system to switch between control of the local application software on the universal controlling device **100** and

control of a computer pointer **420** for the purpose of mousing, i.e., the process of moving a positionable pointer, such as the pointer on a Windows brand PC desktop **422**. To this end, the application software may also include a motion scaling function for use in the pointer control mode. Thus, the application software of the universal controlling device **100** will allow the universal controlling device **100** to operate in a first operational mode, in which the display presents a graphical user interface comprised of icons to control one or more of a plurality of audio-visual equipment (target devices), including a TV, VCR, DVD, satellite box, AV receiver and a HTPC, and a second operational mode, in which a pointer is controlled.

In the first operational mode, the universal controlling device **100** may be used to command various conventional operational functions of the home appliances. For example, the universal controlling device **100** may be used to select a specific media playback device, such as a DVD player **402**, as the input to the AV receiver **406**, resulting in the display of the DVD output on TV **408**. In such a process, 4-way navigation mechanical buttons **510** and center select button **518** would typically be used to navigate through selections and menus displayed on the TV **408**. Additionally, soft buttons displayed on display **504** as well as mechanical buttons **342** would typically be programmed to control operational functions of the DVD player **402**, AV receiver **406**, and the TV **408**, for example as part of a "home theater" mode. Thus, when operating within the first operational mode, when the user activates a mechanical button or soft button, a command code specific to an operational function on a specific target device is typically sent to target device.

Referring now to FIG. 4, in the second operational mode, i.e., the pointer control mode, touch-sensitive digitizing sub-system on the universal controlling device **100** is used as a mousing (pointer control) input device for the HTPC **410**. In one embodiment, a pointer-mode activation button **512**, shown in FIG. 2, allows the universal controlling device **100** to be toggled between the first operational mode and the second operational or pointer control mode. As will be appreciated, one or more of the feedback components of the universal controlling device may be utilized to inform the user as to which of the operational modes the universal controlling device **100** have been configured into as a result of actuation of the pointer-mode activation button **512**.

When the universal controlling device **100** is placed into the pointer control mode, position information output from touch-sensitive digitizer sub-system is converted into a data-stream and is sent via a (RF or IR) transmitter to the USB (RF or IR) receiver converter **412** that is connected to a USB port on the HTPC **410**. USB receiver converter **412** converts the received data-stream into mouse position messages that are sent to the Windows brand operating system of the HTPC **410** via the USB connection. The HTPC **410** may thus use the data provided by the touch-sensitive digitizing sub-system of the universal controlling device **100** identically to data received from a USB mouse, e.g., to control movement of a displayed pointer. This is illustrated in FIG. 4 which demonstrates that, when stylus **506** is moved across the dual-mode display **504**, displayed pointer **420** is moved in a corresponding direction on a HTPC desktop **422** displayed on TV **408**. Further, a scaling function in the software application may be provided to insure that motions made using a stylus or a finger correspond useably to motions of a PC pointer on the HTPC desktop especially in cases where the LCD on the universal controlling device **100** is in portrait orientation and HTPC GUI desktop **422** is in landscape orientation.

In the preferred embodiment, all of the user interface functions typically associated with mousing are included through use of the pointer control mode of the universal controlling device **100** such as: double-tapping to stick the pointer to a window bar, dragging the window across the desktop, and single tapping to release; double-tapping to open a window or start an application; etc. Additionally, with reference to FIG. 1, when the universal controlling device **100** is in pointer control mode, two of the mechanical buttons **514/516** may be programmed to function as the left and right mouse buttons, as per the functions on such buttons on a mouse or on a laptop PC trackpad.

In a yet further embodiment, the universal controlling device **100** may be switched between the first operational mode and the pointer control mode is switched by actuation of a soft button located on LCD display **504**. Still further, the system may be provided with a media management and playback control application running on the HTPC **410** that provides media database browsing and media playback control whereby the advanced remote is used in the first operational mode to conventionally command functional operations of appliances, i.e., a mode wherein graphical user interface elements on the TV display are navigated by using the 4-way switch **510** and center select **518** mechanical buttons, and the second operational mode to command pointer operations. To this end, the system may be adapted wherein the HTPC **410** communicates to the universal controlling device **100** to allow the universal controlling device to toggle between the first operational mode and the pointer control operational mode when the media management and playback control application is entered and exited from the media management and playback control state. For example, when the media management and playback control application is exited, a message may be sent from the application to the universal controlling device **100** via a RF communications link where, upon receipt of this message, the universal controlling device **100** is switched to the pointer control operational mode. It will also be understood that, in cases where the universal controlling device **100** is utilized to command the HTPC **100** to enter and exit the media management and playback control state, the state of the HTPC **100** may be tracked internally within the universal controlling device **100**. For example, when a command is issued from the universal controlling device **100** for the purpose of causing the HTPC **100** to exit the media management and playback control application the universal controlling device **100** is also caused to switch to the pointer control operational mode.

While various concepts have been described in detail, it will be appreciated by those skilled in the art that various modifications and alternatives to those concepts could be developed in light of the overall teachings of the disclosure. For example, the universal controlling device **100** may include a WLAN transceiver subsystem for communicating with and controlling devices connected to a WLAN, including the HTPC **410**. Additionally, while the embodiments presented above are described in the context of a universal controlling device (i.e. a controlling devices capable of commanding the operation of multiple classes of appliances devices from multiple manufacturers) as being most broadly representative of controlling devices in general, it will be appreciated that the teachings of this disclosure may be equally well applied to other controlling devices of narrower capability without departing from the spirit and scope of the present invention. As such, the particular concepts disclosed are meant to be illustrative only and not limiting as to the scope of the invention which is to be given the full breadth of the appended claims and any equivalents thereof.

7

All documents cited within this application for patent are hereby incorporated by reference in their entirety.

What is claimed is:

1. A method for using a universal controlling device comprised of a display having a touch-sensitive surface to transmit data to one or more appliances located remotely from the controlling device, comprising:

causing one or more graphical user interfaces comprised of graphical user interface icons to be displayed in the display of the universal controlling device;

accepting via the touch-sensitive surface of the universal controlling device a first input type indicative of a selection of a displayed graphical user interface icon;

causing the universal controlling device to transmit to the one or more appliances first data representative of the displayed graphical user interface icon selected by the first input type;

accepting via the touch-sensitive surface of the universal controlling device a second input type indicative of a motion made across the touch-sensitive surface;

causing the universal controlling device to transmit to the one or more appliances second data representative of the motion made across the touch-sensitive surface provided by the second input type; and

causing the universal controlling device to distinguish the first input type received via the touch-sensitive surface from the second input type received via the touch-sensitive surface.

8

2. The method as recited in claim 1, wherein the universal controlling device supports a first operational mode and a second operational mode and the universal controlling device uses the first operational mode and the second operational mode to distinguish the first input type received via the touch-sensitive surface from the second input type received via the touch-sensitive surface.

3. The method as recited in claim 2, wherein the universal controlling device automatically toggles between the first operational mode and the second operational mode.

4. The method as recited in claim 3, wherein the universal controlling device automatically toggles between the first operational mode and the second operational mode as a function of a state of the one or more appliances.

5. The method as recited in claim 1, wherein the first data comprises command data for commanding one or more operational functions of the one or more appliances.

6. The method as recited in claim 5, wherein the second data comprises data for causing movement of a displayed cursor associated with the one or more appliances.

7. The method as recited in claim 1, wherein at least one of the first data and the second data are transmitted from the universal controlling device utilizing an IR protocol.

8. The method as recited in claim 1, wherein at least one of the first data and the second data are transmitted from the universal controlling utilizing an RF protocol.

* * * * *