



US007620327B2

(12) **United States Patent**
Snawerdt

(10) **Patent No.:** **US 7,620,327 B2**
(45) **Date of Patent:** ***Nov. 17, 2009**

(54) **FIBER OPTIC TELECOMMUNICATIONS
CARD WITH ENERGY LEVEL MONITORING**

(75) Inventor: **Peter Snawerdt**, Melbourne Beach, FL
(US)

(73) Assignee: **Oyster Optics, Inc.**, West Melbourne,
FL (US)

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 1425 days.

This patent is subject to a terminal dis-
claimer.

(21) Appl. No.: **10/188,643**

(22) Filed: **Jul. 3, 2002**

(65) **Prior Publication Data**

US 2003/0007215 A1 Jan. 9, 2003

Related U.S. Application Data

(60) Provisional application No. 60/303,932, filed on Jul. 9,
2001.

(51) **Int. Cl.**
H04B 10/00 (2006.01)

(52) **U.S. Cl.** **398/164**; 398/135; 398/183

(58) **Field of Classification Search** 398/150-152,
398/164, 183-86, 207, 135, 166-168

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,479,266 A * 10/1984 Eumurian et al. 327/72
4,709,415 A 11/1987 Prisco 455/607

4,754,452 A	6/1988	Henry	
4,824,201 A	4/1989	Kazovsky	380/96.16
4,933,929 A	6/1990	Tajima	370/3
4,998,295 A	3/1991	Siegel	
5,062,704 A *	11/1991	Bateman	356/73.1
5,223,967 A	6/1993	Udd	
5,239,306 A	8/1993	Siwiak et al.	
5,291,516 A	3/1994	Dixon et al.	

(Continued)

FOREIGN PATENT DOCUMENTS

DE 19949401 4/2001

(Continued)

OTHER PUBLICATIONS

www.fotec.com/otdrkit.htm 'Fiber U PC-based OTDR' 1998-2000,
Fotec, Inc.

(Continued)


Primary Examiner—Dzung D Tran

(74) *Attorney, Agent, or Firm*—Davidson, Davidson &
Kappel, LLC

(57) **ABSTRACT**

A transceiver card for a telecommunications box for trans-
mitting data over a first optical fiber and receiving data over a
second optical fiber. The card has transmitter for transmitting
data over the first optical fiber, the transmitter having a laser
and a modulator, a fiber output optically connected to the laser
for connecting the first optical fiber to the card, a fiber input
for connecting the second optical fiber to the card, a receiver
optically connected to the fiber input for receiving data from
the second optical fiber, and an OTDR optically connected
between the transmitter and the fiber output or between the
receiver and the fiber input. An energy level detector is also
provided between the receiver and the fiber input.

39 Claims, 3 Drawing Sheets



U.S. PATENT DOCUMENTS

5,319,438	A	6/1994	Kiasaleh	356/345
5,452,086	A	9/1995	Bunn	
5,455,698	A	10/1995	Udd	
5,479,539	A *	12/1995	Goldsmith et al.	385/14
5,483,370	A	1/1996	Takahashi	359/128
5,539,560	A *	7/1996	Dennis et al.	398/49
5,543,952	A	8/1996	Yonena	
5,561,727	A *	10/1996	Akita et al.	385/88
5,572,350	A	11/1996	Spanke	
5,577,087	A	11/1996	Furuya	375/377
5,606,446	A	2/1997	Davis et al.	
5,625,479	A	4/1997	Suzuki et al.	359/135
5,680,234	A *	10/1997	Darcie et al.	398/9
5,726,784	A	3/1998	Alexander et al.	
5,745,613	A	4/1998	Fukuchi et al.	385/24
5,757,912	A	5/1998	Blow	380/21
5,771,442	A	6/1998	Wang et al.	455/93
5,793,512	A	8/1998	Ryu	
5,825,949	A	10/1998	Choy et al.	
5,896,211	A	4/1999	Watanabe	
5,903,375	A *	5/1999	Horiuchi et al.	398/37
5,907,417	A *	5/1999	Darcie et al.	398/20
5,920,416	A	7/1999	Beylat et al.	
5,923,451	A	7/1999	Karstensen et al.	
5,940,452	A	8/1999	Rich	
5,946,119	A	8/1999	Bergano et al.	
5,953,139	A	9/1999	Nemecek et al.	359/124
5,953,421	A	9/1999	Townsend	380/21
RE36,430	E	12/1999	Halbert-Lassalle et al.	
6,005,694	A *	12/1999	Liu	398/6
6,072,615	A	6/2000	Mamyshev	
6,097,525	A	8/2000	Ono et al.	
6,122,086	A	9/2000	Djupsjobacka	359/181
6,124,960	A	9/2000	Garthe et al.	359/181
6,201,632	B1	3/2001	Rollins	
6,215,565	B1	4/2001	Davis et al.	359/110
6,243,505	B1	6/2001	Bosso et al.	
6,256,130	B1	7/2001	Buelow	
6,271,950	B1	8/2001	Hansen et al.	
6,285,548	B1	9/2001	Hamlet et al.	361/695
6,307,659	B1 *	10/2001	Gilliland et al.	398/135
6,335,814	B1	1/2002	Fuse et al.	
6,362,908	B1	3/2002	Kimbrough et al.	
6,396,605	B1	5/2002	Heflinger et al.	359/154
6,404,528	B1	6/2002	Pfeiffer	359/189
6,469,816	B1	10/2002	Snawerdt	
6,476,952	B1 *	11/2002	Snawerdt	398/141
6,515,777	B1 *	2/2003	Arnold et al.	398/97
6,529,316	B1 *	3/2003	Treyz et al.	359/337.11
6,549,311	B1	4/2003	Hakki et al.	359/124

6,594,055	B2	7/2003	Snawerdt	
6,643,046	B2	11/2003	Ibe et al.	359/238
6,665,500	B2	12/2003	Snawerdt	
6,690,890	B1	2/2004	Udd et al.	
6,842,236	B1	1/2005	Deutsch	356/73
6,990,296	B2	1/2006	Choudhary et al.	398/188
7,035,543	B1	4/2006	Hoshida et al.	398/79
7,099,592	B2 *	8/2006	Snawerdt	398/141
7,200,344	B1	4/2007	Hoshida	398/202
2002/0196501	A1 *	12/2002	Buss et al.	359/152

FOREIGN PATENT DOCUMENTS

EP	0293 086	11/1988
EP	0977382	2/2000
FR	2637432	4/1990
JP	060539-04	2/1994

OTHER PUBLICATIONS

www.tek.com/Measurement/Products/catalog/yseries/index.html
 "Optical Time Domain Reflectometer", Jul. 9, 2001.
 www.youthcom.com/product/instrument/anritsu/mw9076.htm
 "MW9076 series mini-OTDR" 1998-2000.
 Newbridge 3600 MainStreet Family Preinstallation Guide section 10.3 et seq., Mar. 1998, 26 pages.
 STM/S Release 4.0 Documentation, printed from Internet Jan. 17, 2001, date unknown, 21 pages.
 Gary Cloud, Optical Methods in Experimental Mechanics, Part 2: Interference of Light Waves, Jul./Aug. 2002, pp. 13-15.
 "Amplitude Modulation (AM)." Definition, Institute for Telecomm. Sciences. www.its.bldrdoc.gov. Accessed Sep. 3, 2003.
 "Amplitude Intensity Modulation (AIM)." Definition, Institute for Telecomm. Sciences. www.its.bldrdoc.gov. Accessed Sep. 3, 2003.
 Lithium Niobate Intensity (Amplitude Modulator). AT&T Microelectronics. Technical Note, Mar. 1995.
 Newton, Harry, Newton's Telecom Dictionary, Flatiron Publishing, incorporated, 8th edition, pp. 64,544,545, Nov. 2001.
 Swanson et al.: "High Sensitivity Optically Preamplified Direct Detection DPSK Receiver with Active Delay-Line Stabilization," IEEE Photonics Technology Letters, vol. 6, No. 2, Feb. 2004.
 Atia et al.: "Demonstration of Return-to-Zero Signaling in Both OOK and DPSK Formats to Improve Receiver Sensitivity in an Optically Preamplified Receiver," Lincoln Laboratory, Massachusetts Institute of Technology, 1999, pp. 226-227.
 "LiNbO3 Optical Modulators," Operation Manual, Sumitomo Osaka Cement Co., Ltd. Version 1.0, Dec. 13, 1996, 10 pages.
 "SHF 4001 MUX 40 GBit/s Multiplexer," SHF Design, Feb. 15, 1999, 4 pages.
 Terumi Chikama et al.: "Modulation and Demodulation Techniques in Optical Heterodyne PSK Transmission Systems," Journal of Lightwave Technology, vol. 8, No. 3, Mar. 1990, 309-322.

* cited by examiner




Fig. 1




Figure 2




Figure 3

FIBER OPTIC TELECOMMUNICATIONS CARD WITH ENERGY LEVEL MONITORING

Priority to U.S. Provisional Application No. 60/303,932,
filed Jul. 9, 2001 and hereby incorporated by reference herein,
is claimed.

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates generally to telecommunica-
tions and more particularly to transmitters and receivers for
fiber optic networks.

2. Background Information

In current fiber optic networks, an electronic data stream is
fed to an optical fiber multiplexor, which is also called "a
box" in the industry. Each multiplexor runs on a specific
transmission standard, for example, SONET. A laser and an
amplitude modulation circuit for the laser typically are
located on a card, which fits into the box. The laser amplitude
modulator typically pulses or alters the laser output to create
an amplitude-modulated optical signal representative of the
electronic data stream. The laser amplitude modulator and
laser thus define a transmitter for transmitting the optical
signal over an optical fiber. A receiver for the amplitude-
modulated optical signals of the optical data typically
includes a photodiode to convert the optical signals back into
the electronic data stream. Both the transmitter and the
receiver typically are located on the backplane of a single
card, which is replaceable should a component fail.

The card typically also contains a connector for receiving
at least one optical fiber, for example a duplex SC connector.
The connectors normally are located on a faceplate of the
card, the faceplate being perpendicular to the backplane.

The reading of the amplitude-modulated optical data sig-
nals using the photodiode on the card is straightforward: the
optical signals either produce an electric output at the photo-
diode or they do not. As a result, an output electronic data
stream of zeros and ones is generated.

The electronics for the amplitude modulation of the laser
and for the receiving of the optical data on the card thus is
relatively simple. All that is required is a pulsing circuit for
pulsing the laser as a direct function of the input data and a
photodiode for the receiver.

Existing amplitude modulated systems have the disadvan-
tage that the fiber can be easily tapped and are not secure.

U.S. Pat. No. 5,455,698 purports to disclose a secure fiber
optic communications system based on the principles of a
Sagnac interferometer. A data transmitter is a phase modula-
tor for modulating counter-propagating light beams sent by a
receiver round a loop. The receiver includes a light source, a
beamsplitter for splitting light from the light source into
counter-propagating light beams and for receiving the phase-
modulated light beams, and an output detector. U.S. Pat. No.
5,223,967 describes a similar Sagnac-interferometer-based
system operating over a single optical fiber.

The Sagnac-interferometer-based systems described in
these patents have the disadvantage that they require the light
to travel over a loop, whether back and forth in a single fiber
or over a long length looped fiber. As a result, either the link
budget for the single fiber must be doubled, reducing the data
carrying capacity for a single fiber, or else a looped fiber with
significant and expensive extra length of at least twice that of
a single fiber must be laid between the transmitter and the
receiver. Moreover, the receiver contains the light source, as
opposed to the current installed base where the transmitter
has the light source.

The Sagnac-interferometer-based systems thus are expen-
sive to build and operate, and do not work particularly well
with existing multiplexors or card formats.

Several companies currently provide OTDR (optical time-
domain reflectometers) which can monitor an optical fiber
and determine if the presence of and location of a break in the
fiber. Such companies include Youth Communication Co.
with the MW Series Mini-OTDR and OTDR modules from
Tekronix Communications.

These detectors however are expensive and must be
applied to the fiber away from the box.

U.S. Pat. No. 5,777,727 discloses details of OTDR tech-
nology and is hereby incorporated by reference herein.

SUMMARY OF THE PRESENT INVENTION

An object of the present invention is to provide a trans-
ceiver card for providing secure optical data transmission
over optical fiber. Another alternate or additional object of the
present invention is to provide for replacement of existing
cards with a transceiver card permitting ODTR and tapping
detection capabilities.

The present invention provides a transceiver card for trans-
mitting data over a first optical fiber and receiving data over a
second optical fiber, the card having a transmitter for trans-
mitting data over the first optical fiber and a receiver for
receiving data from the second optical fiber, and an OTDR
connected optically to the second optical fiber upstream from
the receiver. Preferably, the OTDR operates at a wavelength
that is different than the wavelength used for data transmis-
sion and is connected in the optical circuit via a wavelength
division multiplexed coupler. By operating the OTDR at a
wavelength different than the wavelength used for data trans-
mission, the OTDR may be allowed to continuously operate
without disruption of the data traffic.

Preferably, an energy level detector is also provided on the
card. The energy level detector is preferably optically con-
nected to the second fiber between the OTDR and the receiver.

The OTDR preferably is monitored by an embedded pro-
cessor within the box. The processor analyzes the OTDR
output data to determine if the characteristics of the optical
fiber system have changed relative to a reference character-
istic. If the optical fiber system has changed relative to the
reference OTDR characteristic, then a degradation of the
optical fiber system, which may indicate a fiber breach or a
fiber tap, can be logged along the position of the degradation
source relative to the location of the OTDR. The indication of
degradation of the fiber system may provide an alarm signal,
for example an electronic signal sent to a network operations
center to indicate the measured degradation of the fiber sys-
tem along with the approximate location of the degradation
point, a light on the outside of the box or a sound-emitting
alarm. Alternatively, the OTDR output may be connected to a
display model via an electrical connection on the card for
display to a human operator, or transferred by the transceiver
to be analyzed at the network operations center.

The transceiver card of the present invention preferably has
fiber span length ranges for operation that are compatible
with standard optical multiplexor operation, for example, two
to twenty kilometers or ten to one hundred kilometers. The
OTDR and energy level detector must have a measurement
dynamic range that ensures proper operation over the span
length limits of the transceiver card. By specifying fiber span
length ranges for the OTDR and energy detector enhanced
transceiver, the cost of implementation of the OTDR and

energy level detector can be optimized with span length thus providing an optimized cost of implementation benefit to the customer.

The present invention thus permits a card-based transmission system incorporating an energy level detector for optical tap detection, which can provide for more secure data transmission than existing amplitude-based cards along with breach localization services from the OTDR. Because of advances in semiconductor and optical component packaging, the OTDR and energy level detector parts along with the optical transmitter and receiver components can fit all on one card compatible with most existing box dimensions.

The transmitter light source preferably is a laser, for example a semiconductor laser operating at a 1550 nm, or other, wavelength.

Preferably, the energy level detector provided on the card for measuring light energy in a fiber is connected electronically to an alarm, so that when a drop or increase in the energy level is detected, which may indicate a tap, the card may provide an alarm signal, for example an electronic signal sent to a network operations center to indicate a drop or increase in the optical energy level, a light on the outside of the box or a sound-emitting alarm. Depending upon the optical transmission method implemented, a successful tap may be placed by adding light to the system through the tapping device. Implementations of the single fiber Sagnac transmission method described in U.S. Pat. No. 5,223,967 may be susceptible to such a tapping method unless an energy level detector that monitors for an increase or decrease in the optical signal level is included as part of the design.

The card includes an optical fiber interface for at least one fiber, and preferably for two fibers. The interface may be a duplex SC connector, for example.

The card preferably is a replacement part for an existing optical multiplexor transceiver card.

The present invention also provides a method for providing a continually-operating or, preferably, a commanded operation OTDR within an existing box including the steps of:

- removing an existing transceiver card; and
- replacing the transceiver card with the card of the present invention.

The present invention also provides a method for manufacturing an optical transceiver card for transmitting data over at least one data transmitting optical fiber, the card having a transmitter and a receiver, the method comprising the steps of:

- placing a transmitter on a printed circuit board,
- placing a receiver on a printed circuit board; and
- placing an OTDR on the printed circuit board.

Preferably, an energy level detector is also placed on the printed circuit board, and a light is connected to a faceplate connected to the printed circuit board, the light indicated a change in energy at the detector or degradation of the optical fiber system.

BRIEF DESCRIPTION OF THE DRAWINGS

A preferred embodiment of the present invention is described below by reference to the following drawings, in which:

FIG. 1 shows schematically a card of the present invention located in an existing telecommunications box, such as a multiplexor; and

FIG. 2 shows a block diagram of the transceiver of the present invention.

FIG. 3 shows a description of an analog energy level detector of the present invention.

DETAILED DESCRIPTION

FIG. 1 shows an existing telecommunications box 2, for example a multiplexor, refitted with a card 1 of the present invention. Box 2 has an electronic data input 3 and output 4, which connect to a motherboard 5 of the box 2. Motherboard 5 includes a bus 6 for connecting existing amplitude-based cards to the motherboard 5, and connects the input 3 and output 4, through for example, data conversion circuitry, to the bus 6. The type of bus 6 is dependent upon the box manufacturer, and different types of boxes, motherboards and buses are well known in the art. Card 1 of the present invention includes electrical connections 8 to fit into bus 6.

Card 1 also includes a faceplate 9 and a backplane 7, which preferably is a printed circuit board. Faceplate 9 may be perpendicular to backplane 7 and be flush with a front side of box 2.

Faceplate 9 may have a fiber connector 109, such as a duplex SC connector, for connecting to an output fiber 110 and an input fiber 111. Alternately, a single fiber for inputting and outputting signals could be provided.

FIG. 2 shows the card 1 of the present invention in more detail. A transmitter 10 transmits signals over optical fiber 110 via output 109A. Transmitter 10 includes a single laser 12, for example a semiconductor laser emitting a narrow band of light at approximately 1550 nm, or at other wavelengths. Light emitted from laser 12 passes through a modulator 16, for example an amplitude or phase modulator, directly next to or part of the same package as laser 12. The light may be depolarized by a depolarizer 14. An electronic controller 18, preferably manufactured directed on the printed circuit board of backplane 7 (FIG. 1), controls modulator 16 and may provide power to laser 12. Input data 19 is fed to the controller 18, which then controls modulator 16 to modulate the light from laser 12 as a function of the input data 19.

The transceiver of the present invention preferably operates in a phase-modulated mode, though conventional amplitude-modulated transmitters and receivers, including those using return-to-zero type signals, for example, may also be used. The phase-modulated signals have the advantage that breach detection by the energy level detector work more effectively, since the amplitude of the optical signal is constant and thus a drop in the optical signal level is more easily detected.

Optical signals are received at an input 109B of connector 109 from fiber 111.

Receiver 11 includes two coupler/splitters 31 and 131, each functioning as a splitter. Splitter 131 is preferably a wavelength division multiplexed coupler/splitter to allow the OTDR 132 to operate at one optical wavelength, for example 1670 nm, while the transmitted data stream 19 and received data stream 34 are carried on a different wavelength, for example 1550 nm. This functionality allows the OTDR 132 on transceiver card 1 to be commanded to continuously operate without interruption or corruption of the received data stream 34. Splitter 131 splits off the wavelength of light applicable to the OTDR into fiber 133, which has an input to OTDR 132. Splitter 31 then splits off a portion of the remaining other light, directing part of the optical energy to an energy level or tap detector 33 and passes the residual light to an optical receiver 32. Optical receiver 32 converts the optical signal from optical to electronic form to recover the electronic data stream 34 as appropriate for the optical modulation technique employed.

OTDR **132** has a control circuit **134** and a bus **135** which allows the device to be controlled by a processor. The OTDR thus can monitor the fiber **111** and provide information through bus **135** to a processor for determining the location of a breach or tap.

Detector **33** monitors the light energy in the fiber **111** via the light energy coupled to the detector by splitter **31**. If the amplitude drops during monitoring, which may indicate a tap, the detector **33** provides an alert and can, for example, send an electronic signal to the processor via bus **135** to indicate a drop or increase in the optical energy level, sound an alarm or alert network maintenance personnel, for example through an LED **133** or by sending an alarm message using transmitter **10**. Another LED **134** can provide an indication of proper signal reception. An energy level detector control circuit **233** controls the alarm threshold and energy detection and provides output indications from the energy detection circuit to a processor via bus **135** which may be shared with the OTDR control circuit **134**.

FIG. **3** shows the energy level detector **33** of the present invention in more detail. The energy level detector **33** described by FIG. **3** represents a preferred analog implementation, with other implementation circuits possible, for bounding the optical energy within an acceptable range with thresholds which may be programmable.

A photodetector or other optical to electrical conversion device **153** measures the optical signal coupled to its input by coupler/splitter **31**. The output of photodetector **153** is an electrical voltage whose level correlates to the optical power at the input to the photodetector **153** based upon the photodetector **153** transfer optical to electrical conversion transfer function. Depending upon the electrical bandwidth of photodetector **153** and the optical signal format present at the input to photodetector **153**, the electrical signal may be filtered by a low pass filter **154** to provide an average voltage level which represents the average optical power measured by photodetector **153**. After filtering the signal, the electrical signal may be conditioned and scaled by either a logarithmic or linear amplifier **155**. Scaling the data may be necessary to ensure that energy level detection can be made without performance degradation over the span length range required for the circuit. The choice of scaling type is chosen primarily based upon the optical to electrical conversion transfer function of the photodetector and the range of expected optical power levels at the photodetector **153** input based upon span length ranges. Generally, the transfer function of semiconductor photodetection devices is exponential with respect to optical to electrical conversion. For such components, the cascade of an exponential photodetector with a logarithmic amplifier offers the advantage of providing a net linear transfer function from optical power at the input to the photodetector to voltage at the logarithmic amplifier. Thus, a digitally programmable detection threshold can be developed which offers the same resolution per bit regardless of the span length of the device.

The electrical signal, after being scaled by the linear or logarithmic amplifier **155**, is compared to reference voltages by one or more comparators. As shown in FIG. **3**, comparator **156** will transition from a low to high output when the voltage output from the logarithmic or linear amplifier **155** exceeds the reference voltage established by the digital to analog (D to A) converter **158**. Conversely, comparator **157** will transition from a low to high output when the voltage output from the logarithmic or linear amplifier **155** falls below the reference voltage established by the digital to analog converter **159**. The output of OR gate **160** will transition from low to high when either the output of comparator **156** or comparator **157** transitions from low to high. For the example of FIG. **3**, an alarm

state is said to exist when the output of OR gate **160** is high. To indicate an alarm state, the OR gate output may trigger an audible alarm via a siren **162**, a visual alarm via a light or light emitting diode (LED) **161** or may indicate an alarm state to the processor via the energy level detector interface **233** and processor bus **135**. The reference voltages established by D to A converters **158** and **159** may be programmable through a digital processor or state machine via a digital bus **135** and an energy level detector interface circuit **233**. One or more thresholds **163** and **164** may be established to provide reference levels for comparison to determine one or more alarm states. Thus, the circuit of FIG. **3** may be configured to monitor in real time the optical power at the receiver **11** for excess light or too little light to indicate a potential optical tap, tamper or other degradation of the optical signal.

A digital circuit equivalent to FIG. **3** may be developed. Analog to digital conversion of the logarithmic or linear amplifier **155** output followed by comparison of the digital result to digital thresholds either via software or digital hardware would indicate optical energy levels within limits or not. Additional filtering via averaging of digital conversions via a moving average or other digital filtering technique could replace or supplement filtering provided by analog filter **154**. A digital implementation also offers information regarding an estimate of the measured optical signal power, both peak and average, by monitoring the analog to digital output via a computer interface.

The component sizes and types will depend upon the type of transmission desired. For example OC-3 cards may vary in size and certain component types from OC-192 cards.

While the cards may be placed in new boxes, the present invention also permits for the removal of existing optical transmission cards to be easily replaced by the enhanced security cards. The fibers are disconnected, the box **2** is simply opened and the amplitude-modulated-based card is removed. The card **1** is inserted into the bus **6** and the fibers are connected.

The card **1** of the present invention may thus provide existing boxes with continual breach localization and detection secure transmission mode capability. Moreover, a separate OTDR which is space-consuming need not be provided.

While the energy level detector must be at the receiver side, the OTDR also could be located on the transmitter side.

What is claimed is:

1. A transceiver card for a telecommunications box for transmitting data over a first optical fiber and receiving data over a second optical fiber, the card comprising:

- a transmitter for transmitting data over the first optical fiber, the transmitter having a laser, a modulator, and a controller receiving input data and controlling the modulator as a function of the input data, the transmitter transmitting optical signals for telecommunication as a function of the input data;
- a fiber output optically connected to the laser for connecting the first optical fiber to the card;
- a fiber input for connecting the second optical fiber to the card;
- a receiver optically connected to the fiber input for receiving data from the second optical fiber; and
- an energy level detector optically connected between the receiver and the fiber input to measure an energy level of the optical signals, wherein the energy level detector includes a plurality of thresholds.

2. The card as recited in claim **1** wherein the energy level detector includes an OR gate.

3. The card as recited in claim **1** wherein the modulator is a phase modulator.

7

4. The card as recited in claim 3 wherein the receiver receives phase-modulated signals.

5. The card as recited in claim 1 wherein the energy level detector includes a photodiode and a liner or logarithmic amplifier scaling an output of the photodiode.

6. The card as recited in claim 1 wherein the thresholds are programmable.

7. The card as recited in claim 1 wherein the energy level detector includes a detector controller capable of setting values for the thresholds.

8. The card as recited in claim 7 wherein the detector controller receives an indication of a threshold being crossed.

9. The card as recited in claim 1 wherein the plurality of thresholds bound an acceptable energy range for the received light.

10. The card as recited in claim 1 wherein the plurality of thresholds indicate a drop in amplitude of a phase-modulated signal.

11. The card as recited in claim 1 wherein the plurality of thresholds indicate an increase in an optical energy level.

12. The card as recited in claim 1 wherein the energy level detector measures optical power.

13. The card as recited in claim 1 further comprising a first splitter splitting the optical signal to the energy level detector, and a second splitter for an OTDR.

14. A transceiver card for a telecommunications box for transmitting data over a first optical fiber and receiving data over a second optical fiber, the card comprising:

a transmitter for transmitting data over the first optical fiber, the transmitter having a laser, a modulator and a controller receiving input data and controlling the modulator as a function of the input data, the transmitter transmitting optical signals for telecommunication as a function of the input data;

a fiber output optically connected to the laser for connecting the first optical fiber to the card;

a fiber input for connecting the second optical fiber to the card;

a receiver optically connected to the fiber input for receiving data from the second optical fiber; and

an energy level detector optically connected between the receiver and the fiber input input to measure an energy level of the optical signals, the energy level detector including a threshold indicating a drop in amplitude of a phase-modulated signal.

15. The card as recited in claim 14 wherein the energy level detector includes an OR gate.

16. The card as recited in claim 14 wherein the modulator is a phase modulator.

17. The card as recited in claim 14 wherein the receiver receives phase-modulated signals.

18. The card as recited in claim 14 wherein the energy level detector includes a photodiode and a liner or logarithmic amplifier scaling an output of the photodiode.

19. The card as recited in claim 14 wherein the threshold is programmable.

20. The card as recited in claim 14 wherein the energy level detector includes a detector controller capable of setting a value for the threshold.

21. The card as recited in claim 20 wherein the detector controller receives an indication of the threshold being crossed.

22. The card as recited in claim 14 wherein the plurality of thresholds bound an acceptable energy range for the received light.

8

23. The card as recited in claim 14 wherein the energy level detector measures optical power.

24. The card as recited in claim 14 further comprising a first splitter splitting the optical signal to the energy level detector, and a second splitter for an OTDR.

25. A transceiver card for a telecommunications box for transmitting data over a first optical fiber and receiving data over a second optical fiber, the card comprising:

a transmitter for transmitting data over the first optical fiber, the transmitter having a laser, a modulator and a controller receiving input data and controlling the modulator as a function of the input data, the transmitter transmitting optical signals for telecommunication as a function of the input data;

a fiber output optically connected to the laser for connecting the first optical fiber to the card;

a fiber input for connecting the second optical fiber to the card;

a receiver optically connected to the fiber input for receiving data from the second optical fiber; and

an energy level detector to measure an energy level of the optical signals, the energy level detector including a threshold indicating a drop in amplitude of a phase-modulated signal.

26. The card as recited in claim 25 wherein the energy level detector includes an OR gate.

27. The card as recited in claim 25 wherein the modulator is a phase modulator.

28. The card as recited in claim 25 wherein the receiver receives phase-modulated signals.

29. The card as recited in claim 25 wherein the energy level detector includes a photodiode and a liner or logarithmic amplifier scaling an output of the photodiode.

30. The card as recited in claim 25 wherein the threshold is programmable.

31. The card as recited in claim 25 wherein the energy level detector includes a detector controller capable of setting a value for the threshold.

32. The card as recited in claim 25 wherein the detector controller receives an indication of the threshold being crossed.

33. The card as recited in claim 25 wherein the plurality of thresholds bound an acceptable energy range for the received light.

34. The card as recited in claim 25 wherein the energy level detector measures optical power.

35. The card as recited in claim 25 further comprising a first splitter splitting the optical signal to the energy level detector, and a second splitter for an OTDR.

36. A transceiver card for a telecommunications box for transmitting data over a first optical fiber and receiving data over a second optical fiber, the card comprising:

a transmitter for transmitting data over the first optical fiber, the transmitter having a laser, a modulator and a controller receiving input data and controlling the modulator as a function of the input data, the transmitter transmitting optical signals for telecommunication as a function of the input data;

a fiber output optically connected to the laser for connecting the first optical fiber to the card;

a fiber input for connecting the second optical fiber to the card;

a receiver optically connected to the fiber input for receiving data from the second optical fiber;

a splitter to split at least a portion of the optical signals to form a split optical signal,

9

a photodetector to measure the split optical signal, the photodetector outputting an electric voltage to correlating to an optical power of the split optical signal, and a detector controller connected electrically to the photodetector.

37. The card as recited in claim **36** wherein the modulator is a phase modulator.

10

38. The card as recited in claim **36** further comprising a photodiode and a linear or logarithmic amplifier scaling an output of the photodiode.

39. The card as recited in claim **36** further comprising a
5 second splitter for an OTDR.

* * * * *

UNITED STATES PATENT AND TRADEMARK OFFICE
CERTIFICATE OF CORRECTION

PATENT NO. : 7,620,327 B2
APPLICATION NO. : 10/188643
DATED : November 17, 2009
INVENTOR(S) : Jean-Daniel Nast


Page 1 of 1

It is certified that error appears in the above-identified patent and that said Letters Patent is hereby corrected as shown below:

Claim 14 in column 7, lines 42 to 43 should read: “an energy level detector optically
connected between the receiver and the fiber input to measure an energy...”

Signed and Sealed this

Sixth Day of April, 2010

A handwritten signature in black ink that reads "David J. Kappos". The signature is written in a cursive, slightly slanted style.

David J. Kappos
Director of the United States Patent and Trademark Office